

## Catalytic Gas Sensor



This item operates on the catalytic combustion principle, and its two arms of electric bridge consists of a test element and a compensate element. The resistance of the test element rises when meeting the combustible gas, in the same time, the output voltage of the bridge changed, the voltage variable is rise in direct proportion as the gas concentration, the compensate element as a reference, and compensate of temperature and humidity.


### Feature Configuration

- \*The bridge output in liner
- \*Fast response
- \*Good reproducibility and selectivity
- \*Working stability
- \*Excellent resistance of H<sub>2</sub>S、 silicon poisoning


### Application

Application in gas concentration detection in industrial field such as natural gas, LPG, coal gas, alkane etc. combustible gas, and gasoline, Alcohol, ketone, benzene etc. organic solvent; Combustible gas leaking alarm or detectors; Gas concentration meter.

### Configuration



### Basic testing circuit



# Datasheet

Item no. 1564474

V1\_06132018\_01\_en

## Specification



Series		Catalytic
Standard cover		Plastic
Working voltage(V)		2.5±0.1
Working current(mA)		150±10
Sensitivity(mV)	1% Methane	20~45
	1% Butane	25~45
	1% Hydrogen	20~40
Liner (%)		≤5
Test range (%LEL)		0~100
Response time (90%)		Less than 10s
Recovery time (90%)		Less than 30s
Working envirenment		-40—+70℃ less than 95%RH
Storage		-20—+70℃ less than 95%RH
Size (mm)		Φ12mm×8mm

This is a publication by Conrad Electronic SE, Klaus-Conrad-Str. 1, D-92240 Hirschau (www.conrad.com).



All rights including translation reserved. Reproduction by any method, e.g. photocopy, microfilming, or the capture in electronic data processing systems require the prior written approval by the editor. Reprinting, also in part, is prohibited. This publication represents the technical status at the time of printing.

© Copyright 2018 by Conrad Electronic SE.



## Sensitivity, response and recovery





## Output signal changed by Tem.



## Output signal changed by Tem.




## Output signal changed by voltage



## Long time stability

The drift in air per year is less than  $\pm 2\text{mV}$ , in 1%CH<sub>4</sub> is less than  $\pm 2\text{mV}$ . For a short period storage (in 2 weeks), the sensor need 30mins'preheating to stabilize. for more than one year storage, it need more than 5 hours peheating.



## Notice

### 1 Must be avoid

#### 1.1 Under the organic silicon

If the sensor face adsorb the organic silicon, its sensing elements will be wrapped, and restrained its sensitivity, also can not recover. The sensor must be avoid in the silicon, fixture, rubber, oily or other plastic additive of silicon.

#### 1.2 Under the High causticity place

The sensor is under the high concentration causticity such as H<sub>2</sub>S, SO<sub>x</sub>, Cl<sub>2</sub>, HCl ect, it not only result the heating material and the sensor lead causticity or broken, but also changed the performance of the sensing material.

#### 1.3 Pollution in alkali, alkali metal salt, halogen

The sensor performance reduced by the pollution of the alkali metal especially brine spray, and under the halogen such as Fluorin.

#### 1.4 Meeting water

If spatter water or dip in the water, it will result of its sensitivity reduced.

#### 1.5 Icing

If water icing on the sensor face, it will result that the sensing material smash and lose its sensitivity.

#### 1.6 High voltage

If the voltage is higher than the value of the sensor or the heater, though the sensor is not broken, it will result that the lead or the heater broken, and make its sensitivity reduced.

## Datasheet

Item no. 1564474

V1\_06132018\_01\_en

---

### **2 Avoid as possible**

#### **2.1 Water coagulation**

In the home, light coagulate water will impact the sensor performance not too much, but if the water coagulated on the face and for some time, the sensitivity will be reduced.

#### **2.2 In the high concentration gas**

Whether the sensor is electrified, the sensor stored in the high concentration gas for a long time, it will impact its sensitivity.

#### **2.3 Long time storage**

The sensor is stored for a long time without electrify, its resistance will be drift ,

And this case is of the storage environment. The sensor must be storage in the seal bag without Any silicon. The sensor is not electrified for storage, it must be electrified for a long time before using.

#### **2.4 under the extremity place for a long time**

Whether the sensor is electrified, under the extremity place for a long time such as high temperature, high humidity, or high pollution ext, it will impact the sensor performance heavily.

#### **2.5 Vibration**

Vibration frequently or excessively, it will impact the sensor lead broken. And the vibration also will be happened in the transportation or assembling or welding process.

#### **2.6 Concussion**

If the sensor is struck heavily, it will make the lead broken.

#### **2.7 Using**

It is better of welding by hand for a sensor.

If you used the wave welding, please satisfied the conditions as below:

2.7.1 Welding assist: Include the least rosin

2.7.2 Speed: 1-2m/min

2.7.3 Preheating temperature:  $100 \pm 20^{\circ}\text{C}$

2.7.4 Welding temperature:  $250 \pm 10^{\circ}\text{C}$

2.7.5 1time passed the machine

If you disobey the conditions, it will impact the sensor sensitivity.